# SHOOO4P Ozone Water Generator



**Operating Instruction** 

Please read this manual carefully before use

## 1.Introduction

Thank you for purchasing the smart ozone generator. In order to use the smart ozone generator correctly, please read the instruction manual carefully before using it. It is simple in design and operation. It is solid and durable, with low noise when it's work. (For nonprofessional maintenance personnel, please don't disassemble the machine.)

# 2.Advantages

- 1. 5.0-8.0 PPM higher concentration ozone water.
- 2. Built-in PSA oxygen concentrator.
- 3. Built-in air compressor.

Built-in air dryer to extended service life.
Built-in venturi tube to dissolve ozone in water.

- 6. Automatic built-in air pressure sensor.
- 7. Easy to install and operate.

## 3.Product Features

- 1. 304 stainless steel cabinet
- 2. Built-in PSA oxygen concentrator
- 3. Oxygen flow: 1.0 LPM

#### 5.Product Display



### 6.Installation and Operation

1. Check that all accessories are included in the package.

2. Connect the equipment (in the machine section).

3. Connect the pipe and clamp it completely with the machine.

4. Press the on/off button (located at the top of the device);

5. Turn on the tap water.

The equipment will start working.

6. If the equipment is not used for a long

time, please turn off the switch and remove it The adapter.

## 7.Use Place

1. Wash fruits and vegetables to remove bacteria, viruses, and surface residues The pesticides.

2. Purify water quality and remove bacteria and viruses from water.

3. Washing clothes, because of the effect of disinfection ozone, there is no chemical formation.

It is suitable for washing clothes for babies. 4. Wash your face and rinse your mouth to remove mite oil from your face. The upper part of the mouth and mouth. Bacteria to make it healthier.

Clean your pet with ozone water to prevent skin problems and fleas.



Installation Precautions

1. Do not plug foreign bodies into the air outlet of the ozone water machine to avoid danger. .

2. Users shall not alter any device of the original product by themselves.

3, there is high pressure in the machine, do not open the cover casually, do not extend the hand or objects into the swing leaf, in case of electric shock. 4. Built-in air compressor

- 5. Built-in air dryer can extend the service life
- of ozone generator
- 6.High concentration ozone water 5.0-8.0 PPM

- 7. Built-in Venturi tube
- 8. Built-in flow sensor
- 9. LED display

10. Type of pipe connection

11. wall

12.Non-contact automatic standby and sleep system

13.CE certification (LVD and EMS)

14. In line with the ROHS

## 4.Product Parameters

Product Model:	SHO004P
Ozone Production:	5000mg/H
Water Pressure:	>3.0Bar
Temperature:	5-30°
Ozone Waterflow:	200-1200L/H
Ozone Water Concentration:	5.0~8.0PP
Power:	350W
Voltage:	220V; 50/60HZ
Size:	L 410xW 155xH 355MM
Weight:	14KG

4. In case of any abnormal situation during the use of the product, please cut off the power supply immediately and contact the after-sale service of the company.